



## **Procedure to delete and re-set limits on the Somfy IO motor**

### **Deleting memory:**

1. With the power already on:
2. Turn **off** for **2** seconds
3. Turn **on** for **8** seconds
4. Turn **off** for **2** seconds, then back on.
5. The awning should start to come out on its own for a short distance and then stop.
6. Using the remote control, press and hold the program button on the back for **7** seconds (do not release). The awning should do 2 double shunts.
7. The awning motor's memory is now deleted.

### **Programme the limits:**

1. Press the up and down buttons together and the awning will do a double shunt.
2. Press and hold the down button for 2 seconds, the awning will come out.
3. Stop the awning (press the 'MY' button) in the desired position remembering to leave a small gap in the knuckles of the arms.
4. Press the 'MY' and the 'In' button simultaneously and the awning will retract in. When fully in press the 'MY' button again and the awning will shunt.
5. To save the limit settings, press the programme button on the back of the remote and the awning will do a double shunt.
6. The awning is now programmed.